


Error: SSH CONN ERROR: Cannot read property bold of undefined

511 Nesvin KN January 23, 2025 [Common Errors & Troubleshooting](#) 2261

How to fix "SSH CONN ERROR: Cannot read property 'bold' of undefined" error in Ezeelogin WebSSH

Overview: This article explains how to resolve the "SSH CONN ERROR: Cannot read property 'bold' of undefined" error in Ezeelogin WebSSH by debugging the WebSSH console, verifying SSH connectivity, and updating the SSH configuration file.



Refer below article to configure and troubleshoot WebSSH in Ezeelogin.

<https://www.ezeelogin.com/kb/article/setup-web-ssh-console-in-ezeelogin-and-ssh-via-browser-180.html>

<https://www.ezeelogin.com/kb/article/could-not-setup-ezeelogin-web-ssh-service-156.html>

Start the WebSSH Console node application manually to determine any errors.

```
root@gateway ~]# DEBUG=* PORT=52222 node $(awk '/^system_folder/ {print $2}'  
/usr/local/etc/ezlogin/ez.conf)/application/external/webssh/index.js
```

If the debug shows the below error then refer below steps to fix the issue.

```
WebSSH2 Logout: user=eztest from=192.168.1.1 host=127.0.0.1 port=36000  
sessionID=undefined/uZDvv6Fk6KiLwsOcAAAA allowreplay=undefined term=xterm-color  
socket.io:client ignoring packet write {"type":2,"data":["ssherror","SSH CONN END BY HOST: All  
configured authentication methods failed"],"nsp":"/"} +2ms
```

In the above example, the user "eztest" tries to access the WebSSH console, and the error

"SSH CONN ERROR: Cannot read property 'bold' of undefined" appears in the console.

In the debug output, it shows "All configured authentication methods failed" for the same user, "eztest".

Follow below steps to fix the above error:

Step 1. Try to manually SSH from the gateway machine as the Ezeelogin user to localhost to confirm it is working. Additionally, ensure that password authentication is enabled for Ezeelogin users.

```
root@gateway ~]# ssh ezlogin_user@localhost
```

Step 2. If the user cannot manually SSH, allow the Ezeelogin user group in the configuration file to resolve the error. Add the following line under **Match Address 127.0.0.1**.

```
root@gateway ~]# vim /etc/ssh/sshd_config
```

```
Match Address 127.0.0.1
```

```
PubkeyAuthentication yes
```

```
PasswordAuthentication yes
```

```
Allowgroups ezuser
```

Step 3. Restart SSH daemon and try to ssh from the gateway machine as the Ezeelogin user to localhost to confirm it's working fine (refer step 1). Then click on the webssh icon on the Ezeelogin software GUI to make sure it works.

Related Articles:

["Blank page" error in webssh console](#)

Online URL:

<https://www.ezeelogin.com/kb/article/error-ssh-conn-error-cannot-read-property-bold-of-undefined-511.html>